

इंटरनेट

मानक

Disclosure to Promote the Right To Information

Whereas the Parliament of India has set out to provide a practical regime of right to information for citizens to secure access to information under the control of public authorities, in order to promote transparency and accountability in the working of every public authority, and whereas the attached publication of the Bureau of Indian Standards is of particular interest to the public, particularly disadvantaged communities and those engaged in the pursuit of education and knowledge, the attached public safety standard is made available to promote the timely dissemination of this information in an accurate manner to the public.

“जानने का अधिकार, जीने का अधिकार”

Mazdoor Kisan Shakti Sangathan

“The Right to Information, The Right to Live”

“पुराने को छोड़ नये के तरफ”

Jawaharlal Nehru

“Step Out From the Old to the New”

IS 10161 (1982): Moving coil voltage regulators [ETD 16: Transformers]



“ज्ञान से एक नये भारत का निर्माण”

Satyanarayan Gangaram Pitroda

“Invent a New India Using Knowledge”



“ज्ञान एक ऐसा खजाना है जो कभी चुराया नहीं जा सकता है”

Bhartrhari—Nitiśatakam

“Knowledge is such a treasure which cannot be stolen”

BLANK PAGE



IS : 10161 - 1982

Indian Standard

“पुनर्विचारित १९८६”
“RE-AFFIRMED 1996”

SPECIFICATION FOR
MOVING COIL VOLTAGE REGULATORS

UDC 621.316.722



© Copyright 1982

INDIAN STANDARDS INSTITUTION
MANAK BHAVAN, 9 BAHADUR SHAH ZAFAR MARG
NEW DELHI 110002

Indian Standard

SPECIFICATION FOR MOVING COIL VOLTAGE REGULATORS

Transformers Sectional Committee, ETDC 16

<i>Chairman</i>	<i>Representing</i>
SHRI C. R. VARIER	Crompton Greaves Ltd, Bombay
<i>Members</i>	
SHRI S. V. MANERIKAR (<i>Alternate</i> to Shri C. R. Varier)	Directorate General of Supplies & Disposals (Inspection Wing), New Delhi
SHRI R. S. ARORA	SHRI D. R. CHANDRAN (<i>Alternate</i>) Gujarat Electricity Board, Vadodara
SHRI A. V. BHEEMARAO	SHRI S. H. MAKHIJANI (<i>Alternate</i>) Calcutta Electric Supply Corporation Ltd, Calcutta
SHRI A. CHATTERJEE	SHRI T. K. GHOSH (<i>Alternate</i>) Bombay Electric Supply and Transport Under- taking, Bombay
SHRI T. K. GHOSH (<i>Alternate</i>)	SHRI S. D. CHOTRANEY
SHRI S. D. CHOTRANEY	SHRI Y. K. PALVANKAR (<i>Alternate</i>) The General Electric Co of India Ltd, Allahabad
SHRI Y. K. PALVANKAR (<i>Alternate</i>)	SHRI D. DHAR
SHRI D. DHAR	SHRI B. A. SUBRAMANYAM (<i>Alternate</i>) Central Power Research Institute, Bangalore
SHRI B. A. SUBRAMANYAM (<i>Alternate</i>)	DIRECTOR
DIRECTOR	SHRI C. S. SARMA (<i>Alternate</i>) Central Electricity Authority, New Delhi
SHRI C. S. SARMA (<i>Alternate</i>)	DIRECTOR (SUBSTATION)
DIRECTOR (SUBSTATION)	DEPUTY DIRECTOR (SUBSTATION) (<i>Alternate</i>) Research, Designs and Standards Organization, Lucknow
DEPUTY DIRECTOR (SUBSTATION) (<i>Alternate</i>)	JOINT DIRECTOR II (SUBSTATION)
JOINT DIRECTOR II (SUBSTATION)	DEPUTY DIRECTOR STANDARDS (ELEC) (<i>Alternate</i>)
DEPUTY DIRECTOR STANDARDS (ELEC) (<i>Alternate</i>)	SHRI G. L. DUA
SHRI G. L. DUA	Rural Electrification Corporation Ltd, New Delhi
SHRI S. C. KHURANA (<i>Alternate</i>)	DR M. V. JOSHI
DR M. V. JOSHI	SHRI P. K. JOSHI (<i>Alternate</i>) Tata Hydro-Electric Power Supply Co Ltd, Bombay
SHRI P. K. JOSHI (<i>Alternate</i>)	SHRI D. B. MEHTA
SHRI D. B. MEHTA	SHRI R. CHANDRAMOULI (<i>Alternate</i>)
SHRI R. CHANDRAMOULI (<i>Alternate</i>)	

(Continued on page 2)

© Copyright 1982

INDIAN STANDARDS INSTITUTION

This publication is protected under the *Indian Copyright Act* (XIV of 1957) and reproduction in whole or in part by any means except with written permission of the publisher shall be deemed to be an infringement of copyright under the said Act.

(Continued from page 1)

<i>Members</i>	<i>Representing</i>
SHRI M. L. MITTAL	Bharat Heavy Electricals Ltd, Bhopal
SHRI PREM CHAND (<i>Alternate I</i>)	
SHRI D. P. GUPTA (<i>Alternate II</i>)	
SHRI T. OM KUMAR	NGEF Ltd, Bangalore
SHRI P. S. RAMAN (<i>Alternate</i>)	
DR G. M. PHADKE	Indian Electrical Manufacturers' Association, Bombay
SHRI P. K. PHILIP (<i>Alternate</i>)	
SHRI V. N. PRAHLAD	Voltas Ltd, Pune
SHRI T. B. SEN (<i>Alternate</i>)	
SHRI CHANDRA K. ROHATGI	Pradip Lamp Works, Patna
SHRI P. S. SAWHNEY	Delhi Electricity Supply Undertaking, New Delhi
SHRI B. B. DASS (<i>Alternate</i>)	
SHRI R. K. SEHGAL	Bombay Suburban Electric Supply Ltd, Bombay
SHRI H. S. NATARAJAN (<i>Alternate</i>)	
SHRI R. G. PARDHANANI	Bharat Bijlee Ltd, Bombay
SHRI V. S. PATIL (<i>Alternate</i>)	
SUPERINTENDING ENGINEER (TECHNICAL PROJECTS)	Andhra Pradesh State Electricity Department (Electricity Projects and Board), Hyderabad
SUPERINTENDING ENGINEER (GRID OPERATION) (<i>Alternate</i>)	
DR VAKIL AHMED	Directorate General of Technical Development, New Delhi
SHRI S. K. PALHAN (<i>Alternate</i>)	
SHRI T. V. VIDYABATNA RAJ	Kirloskar Electric Co Ltd, Bangalore
SHRI M. D. KALLIANPUR (<i>Alternate</i>)	
SHRI S. P. SACHDEV, Director (Elec tech)	Director General, ISI (<i>Ex-officio Member</i>)

Secretary

SHRI K. M. BHATIA
Deputy Director (Elec tech), ISI

Panel for Small Transformers, ETDC 16/P7

Convener

SHRI CHANDRA K. ROHATGI Pradip Lamp Works, Patna

Members

SHRI JAI KUMAR AGARWAL	Shanto Electronics, New Delhi
SHRI V. N. ARORA	Rectifiers & Electronics, New Delhi
SHRI V. S. CHANDRASEKHAR	Kelvinator of India Ltd, Faridabad
PROF A. K. MEHTA (<i>Alternate</i>)	
SHRI S. V. DAMLE	Automatic Electric Ltd, Bombay
SHRI D. N. CHAKRABARTY (<i>Alternate</i>)	
SHRI B. K. GARODIA	International Electricals, Faridabad

(Continued on page 10)

Indian Standard

SPECIFICATION FOR MOVING COIL VOLTAGE REGULATORS

0. FOREWORD

0.1 This Indian Standard was adopted by the Indian Standards Institution on 28 April 1982, after the draft finalized by the Transformers Sectional Committee had been approved by the Electrotechnical Division Council.

0.2 Moving coil voltage regulators are extensively used either to get the constant output voltage with a variable range of input voltage or to get variable output voltage with a constant input voltage depending on their design.

0.3 The harmonics and wave-form distortion introduced by the use of this type of regulators may be taken care of by the user, if required.

0.4 This standard is to be read in conjunction with IS : 2026 (Part I)-1977*, IS : 2026 (Part II)-1977†, IS : 2026 (Part III)-1981‡ and IS : 2026 (Part IV)-1977§. Should, however, any deviation exist between the requirements of IS : 2026 (Part I)-1977*, IS : 2026 (Part II)-1977†, IS : 2026 (Part III)-1981‡, IS : 2026 (Part IV)-1977§ and those of this standard, the provision of the latter shall apply.

0.5 For the purpose of deciding whether a particular requirement of this standard is complied with, the final value, observed or calculated, expressing the result of a test, shall be rounded off in accordance with IS : 2-1960||. The number of significant places retained in the rounded off value should be the same as that of the specified value in this standard.

1. SCOPE

1.1 This standard covers the requirements and methods of tests for moving coil voltage regulators of voltage ratings up to and including 33 kV.

*Specification for power transformers : Part I General (*first revision*).

†Specification for power transformers : Part II Temperature-rise (*first revision*).

‡Specification for power transformers : Part III Insulation level and dielectric tests (*second revision*).

§Specification for power transformers : Part IV Terminal markings, tappings and connections (*first revision*).

||Rules for rounding off numerical values (*revised*).

2. TERMINOLOGY

2.0 For the purpose of this standard, the definitions given in IS : 1885 (Part XXXVIII)-1977* in addition to the following shall apply.

2.1 Moving Coil Voltage Regulator (MCVR) — A piece of apparatus with one short-circuited moving coil which offers buck or boost to the applied voltage by moving the position of the coil.

2.2 Dry Type MCVR — MCVR having the core and windings directly exposed to air or to a gas substantially at atmospheric pressure.

2.3 Oil Immersed MCVR — MCVR having the core and windings immersed in a mineral oil.

2.4 Fixed Coil — A coil which receives the input voltage and is stationary.

2.5 Booster Coil — A coil connected to the fixed coil in such a way that it gives boost to the input voltage.

2.6 Buck Coil — A coil connected to the fixed coil in such a way that it gives buck to the input voltage.

2.7 Moving Coil — A short-circuited coil which is free to move up and down along the axis of the core and fixed coils.

2.8 Manually Operated MCVR — MCVR in which the moving coil is moved with an external handle or other suitable arrangement, including power assisted drive.

2.9 Automatically Operated MCVR — MCVR in which movement of moving coil is automatically controlled to give designed output voltage or the range of voltages.

2.10 Rated Input Voltage — Constant or variable no-load input voltage specified for the MCVR.

2.11 Rated Output Voltage — Constant or variable no-load output voltage specified for the MCVR.

2.12 Rated Current — Maximum continuous full load current which a winding is assigned to carry.

2.13 Rated kVA — The product of rated constant voltage, rated current and the appropriate phase factor.

NOTE 1 — Rated constant voltage shall be either rated input or rated output voltage whichever is specified as constant and the rated current shall be the current assigned to the rated constant voltage winding.

NOTE 2 — Phase factors for single and three phase supply are 1 and 1.73 respectively.

*Electrotechnical vocabulary : Part XXXVIII Transformers (*first revision*).

3. COOLING

3.1 The methods of cooling employed and their identification shall be in accordance with 2 of IS : 2026 (Part II)-1977*.

4. SERVICE CONDITIONS

4.1 The provisions of 3 of IS : 2026 (Part I)-1977† and 3.2 of IS : 2026 (Part II)-1977* shall be applicable.

5. RATINGS

5.1 **Rated kVA** — The provisions of 4.2 of IS : 2026 (Part I)-1977† shall be applicable.

5.2 **Rated Voltage**—Rated voltage shall be as specified by the purchaser.

5.3 **Rated Frequency** — The rated frequency shall be 50Hz.

6. CONSTRUCTION

6.1 MCVR shall have a suitable enclosure, which shall be provided with two independent earthing terminals.

6.2 In case of power assisted drive, provision may be made, when required by the user, for operation with external handle also. In such a case suitable inter-locking shall be provided with the power operating system to ensure the safety of the operator.

6.3 **Fixed Coil** — It shall consist of two sections wound on the same core, one above the other and connected in series opposition. It shall be concentric with the moving coil and the core.

7. LIMITS OF TEMPERATURE RISE

7.1 The temperature rise of the MCVR winding and core shall be in accordance with 3 of IS : 2026 (Part II)-1977*.

8. INSULATION LEVELS

8.1 The insulation levels and corresponding test voltages shall be in accordance with Table 1.

9. TERMINAL MARKING AND RATING PLATE

9.1 The input and output terminals shall be marked in accordance with IS : 2026 (Part IV)-1977‡.

*Specification for power transformers : Part II Temperature-rise (*first revision*).

†Specification for power transformers : Part I General (*first revision*).

‡Specification for power transformers : Part IV Terminal markings, tappings and connections (*first revision*).

TABLE 1 INSULATION LEVELS AND TEST VOLTAGES

(Clause 8.1)

HIGHEST SPECIFIED VOLTAGE (INPUT OR OUTPUT)	IMPULSE TEST VOLTAGE (1.2/50 μ s Wave Shape)	POWER FREQUENCY TEST VOLTAGE (WITHSTAND VALUE FOR 1 min)
(1)	(2)	(3)
kV	kV peak	kV
Less than 1.1	—	2.5
1.1	—	3
3.6	40	10
7.2	60	20
12	75	28
17.5	95	38
24	125	50
36	170	70

NOTE — Moving coil shall not be subjected to the above tests as its terminals are not brought out.

9.2 Each MCVR shall be provided with a rating plate of weatherproof material, fitted in a visible position showing the information given in 9.3. The entries on the rating plate shall be indelibly marked (for example by etching, engraving or stamping).

9.3 Rating Plate — The information to be given on the rating plate shall be as under:

- a) Name of equipment, namely, moving coil voltage regulator;
- b) Number of this standard, Ref IS : 10161;
- c) Manufacturer's name;
- d) Manufacturer's serial number;
- e) Number of phases;
- f) Year of manufacture;
- g) Rated kVA;
- h) Rated frequency;
- j) Rated input voltage with range as applicable;
- k) Rated output voltage with range as applicable;
- m) Rated input and rated output current;
- n) Type of cooling;

- p) Total mass; and
- q) Mass and volume of insulating oil.

9.3.1 The following information relevant to control motors shall also be given to the extent applicable:

- a) Rated kW,
- b) Rated voltage,
- c) Type of supply, and
- d) Number of phases.

9.4 Moving Coil Voltage Regulators may also be marked with ISI Certification Mark.

NOTE — The use of the ISI Certification Mark is governed by the provisions of the Indian Standards Institution (Certification Marks) Act and the Rules and Regulations made thereunder. The ISI Mark on products covered by an Indian Standard conveys the assurance that they have been produced to comply with the requirements of that standard under a well-defined system of inspection, testing and quality control which is devised and supervised by ISI and operated by the producer. ISI marked products are also continuously checked by ISI for conformity to that standard as a further safeguard. Details of conditions under which a licence for the use of the ISI Certification Mark may be granted to manufacturers or processors, may be obtained from the Indian Standards Institution.

10. FITTINGS

10.1 The fittings to be provided with MCVR shall be in accordance with Appendix C of IS : 2026 (Part I)-1977* with the exception that providing dehydrating breather and conservator shall be optional for all ratings.

11. TOLERANCES

11.1 Unless otherwise specified, the tolerances on the declared values shall be in accordance with Table 7 of IS : 2026 (Part I)-1977*.

12. TESTS

12.0 Unless otherwise mentioned in this standard, the tests shall be carried out in accordance with the test methods specified in IS : 2026 (Part I)-1977*, IS : 2026 (Part II)-1977†, and IS : 2026 (Part III)- 1981‡, as applicable.

12.1 Type Tests — The following shall constitute the type tests:

- a) Measurement of winding resistance;

*Specification for power transformers : Part I General (*first revision*).

†Specification for power transformers : Part II Temperature-rise (*first revision*).

‡Specification for power transformers : Part III Insulation level and dielectric tests (*second revision*).

- b) No-load voltage and no-load current at maximum and minimum positions (12.3);
- c) Measurement of no-load loss at maximum and minimum positions;
- d) Measurement of load-loss and impedance voltage at the maximum and minimum positions,
- e) Measurement of insulation resistance;
- f) Induced over-voltage withstand test with moving coil at maximum and minimum positions;
- g) Separate source voltage withstand test;
- h) Temperature rise test at maximum loss position;
- j) Lightning impulse test;
- k) Rate of correction of voltage (applicable to automatic MCVR only) (12.4); and
- m) Test for continuous operation (applicable to automatic MCVR only) (12.5).

12.1.1 For type tests, the number of samples of MCVR of same rating, design and type shall be as given below:

<i>kVA Rating</i>	<i>Number of Samples</i>
Up to 10	2
Above 10	1

Sample(s) shall pass all the tests mentioned in 12.1 for proving conformity to the requirements of this standard. If any of the samples fail(s) in any of the type tests, testing authority, at its discretion, may call for fresh samples not exceeding twice the original number and subject them again to all the tests in which failure had occurred. No single failure shall be permitted in the repeat test(s).

12.2 Routine Tests — The following shall comprise the routine tests:

- a) Measurement of winding resistance,
- b) No-load voltage and no load current at maximum and minimum positions (12.3),
- c) Measurement of no-load loss in maximum and minimum positions,
- d) Measurement of load loss and impedance voltage,
- e) Measurement of insulation resistance,
- f) Induced over-voltage withstand test with moving coil in maximum and minimum positions, and
- g) Separate source voltage withstand test.

12.3 No-load Voltages and No-load Current at Maximum and Minimum Positions

12.3.1 In case of MCVR suitable for giving constant output voltage, the input voltage shall be varied from minimum to maximum as given on the rating plate. For manually operated MCVR, unless otherwise specified by the purchaser, it shall be possible to get the rated voltage when the input voltage remains within the specified voltage. For automatically operated MCVR, the output voltage shall remain within ± 2 percent of the rated voltage.

12.3.2 For MCVR designed to give variable output voltage, the rated voltage shall be applied to the input terminals and the positions of the coil shall be varied from minimum to maximum.

MCVR shall be capable of giving the specified voltage range.

NOTE — Ratio measurement may be used wherever appropriate to show that the required range of voltages is met at no load.

12.3.3 The values of no-load current shall be noted down at the minimum and maximum positions of the no-load voltages. The no-load current shall not be more than 20 percent of the specified full load current for these positions.

12.4 Rate of Correction of Voltage — Time taken for the moving coil to move from one position to the other to give the requisite voltage range from minimum to maximum shall be noted. The voltage range divided by the time so taken shall be taken as the rate of correction of voltage. The test shall be repeated for positions from highest to the lowest voltage range. The value for rate of correction of voltage shall be as agreed between the purchaser and the supplier.

12.5 Test for Continuous Operation — MCVR shall be subjected to a continuous run for a period of one hour, the voltage being changed from one end to the other at the rate of correction of voltage as obtained in

12.4. After this period, measurement of insulation resistance and no-load voltage test shall be repeated.

(Continued from page 2)

Members

SHRI L. M. MATHUR
SHRI V. P. BABBAR (*Alternate*)
SHRI R. V. NARAYANAN

SHRI J. K. GUPTA (*Alternate*)
SHRI R. NATARAJAN
SHRI S. L. NARASIMHAN (*Alternate*)
SHRI PRADEEP KUMAR

SHRI SATYA PAL
SHRI M. M. JOAG (*Alternate*)
SHRI V. SWAMINATHAN
SHRI H. K. AGARWAL (*Alternate*).

Representing

Regional Testing Centre, New Delhi
Directorate General of Supplies & Disposals, New
Delhi
Central Public Works Department, New Delhi
Haryana Electronic Industries Association,
Ambala Cantt
Voltas Ltd, New Delhi
Electronics Ltd, Faridabad

INDIAN STANDARDS

ON

TRANSFORMERS

IS:

- 1180 Outdoor type three-phase distribution transformers up to and including 100 kVA
11 kV :
(Part I)-1981 Non sealed type (*second revision*)
(Part II)-1979 Sealed type
- 1885 (Part XXXVIII)-1977 Electrotechnical vocabulary : Part XXXVIII Trans-
formers (*first revision*)
- 2026 Power transformers :
(Part I)-1977 General (*first revision*)
(Part II)-1977 Temperature-rise (*first revision*)
(Part III)-1981 Insulation level and dielectric tests (*second revision*)
(Part IV)-1977 Terminal marking, tappings and connections (*first revision*)
- 2772 (Part I)-1964 Non-flameproof mining transformers for use below ground:
Part I Oil-immersed type
- 3151-1965 Earthing transformers
- 3639-1966 Fittings and accessories for power transformers
- 5553 Reactors :
(Part I)-1970 Shunt reactors
(Part II)-1970 Series reactors
(Part III)-1970 Neutral earthing reactor and arc suppression coil
- 6600-1972 Guide for loading of oil-immersed transformers
- 8447-1977 Manually operated voltage regulators for domestic use
- 8448-1977 Automatic line voltage correctors (step type for domestic use)
- 8468-1977 On-load tap-changers
- 8478-1977 Application guide for on-load tap-changers
- 9147-1979 Cable sealing boxes for oil immersed transformers suitable for paper insula-
ted lead sheathed cables for highest system voltages from 12 kV up to and
including 36 kV

INDIAN STANDARDS INSTITUTION

Manak Bhavan, 9 Bahadur Shah Zafar Marg, NEW DELHI 110002

Telephones : 26 60 21, 27 01 31

Telegrams : Manaksanstha

Regional Offices :

Western : Novelty Chambers, Grant Road
Eastern : 5 Chowringhee Approach
Southern : C. I. T. Campus
Northern : B69, Phase VII

	Telephone
BOMBAY 400007	37 97 29
CALCUTTA 700072	27 50 90
MADRAS 600113	41 24 48
S. A. S. NAGAR (MOHALI) 160051	—

Branch Offices :

* Pushpak *, Nurmohamed Shaikh Marg, Khanpur
F Block, Unity Bldg, Narasimharaja Square
Gangotri Complex, Bhadbhada Road, T. T. Nagar
22E Kalpana Area
5-8-56C L. N. Gupta Marg
R14 Yudhister Marg, C Scheme
117/418 B Sarvodaya Nagar
Patliputra Industrial Estate
Hantex Bldg (2nd Floor), Rly Station Road

AHMADABAD 380001	2 03 91
BANGALORE 560002	22 48 05
BHOPAL 462003	6 27 16
BHUBANESHWAR 751014	5 36 27
HYDERABAD 500001	22 10 83
JAIPUR 302005	6 98 32
KANPUR 208005	472 92
PATNA 800013	6 28 08
TRIVANDRUM 695001	82 27