

इंटरनेट

मानक

Disclosure to Promote the Right To Information

Whereas the Parliament of India has set out to provide a practical regime of right to information for citizens to secure access to information under the control of public authorities, in order to promote transparency and accountability in the working of every public authority, and whereas the attached publication of the Bureau of Indian Standards is of particular interest to the public, particularly disadvantaged communities and those engaged in the pursuit of education and knowledge, the attached public safety standard is made available to promote the timely dissemination of this information in an accurate manner to the public.

“जानने का अधिकार, जीने का अधिकार”

Mazdoor Kisan Shakti Sangathan

“The Right to Information, The Right to Live”

“पुराने को छोड़ नये के तरफ”

Jawaharlal Nehru

“Step Out From the Old to the New”

IS 15885-2-13 (2012): Safety of Lamp Controlgear, Part 2: Particular Requirements, Section 13: d.c. Supplied Electronic Controlgear for LED Modules [ETD 23: Electric Lamps and their Auxiliaries]



“ज्ञान से एक नये भारत का निर्माण”

Satyanarayan Gangaram Pitroda

“Invent a New India Using Knowledge”



“ज्ञान एक ऐसा खजाना है जो कभी चुराया नहीं जा सकता है”

Bhartrhari—Nitiśatakam

“Knowledge is such a treasure which cannot be stolen”

BLANK PAGE



IS 15885 (Part 2/Sec 13) : 2012

भारतीय मानक

लैम्प नियंत्रणगियर की सुरक्षा

भाग 2 विशिष्ट अपेक्षाएँ

अनुभाग 13 एल ई डी मॉड्यूलों के लिए डी.सी. या ए.सी.
सप्लाई वाले इलेक्ट्रॉनी नियंत्रणगियर

Indian Standard

SAFETY OF LAMP CONTROLGEAR

PART 2 PARTICULAR REQUIREMENTS

Section 13 d.c. or a.c. Supplied Electronic Controlgear for LED Modules

ICS 29.140.99

© BIS 2012

BUREAU OF INDIAN STANDARDS
MANAK BHAVAN, 9 BAHADUR SHAH ZAFAR MARG
NEW DELHI 110002

February 2012

Price Group 3

FOREWORD

This Indian Standard (Part 2/Sec 13) was adopted by the Bureau of Indian Standards, after the draft finalized by the Electric Lamps and Their Auxiliaries Sectional Committee had been approved by the Electrotechnical Division Council.

This standard specifies the general and safety requirements for d.c. or a.c. supplied electronic controlgear for LED modules for supply voltages up to and including 1 000 V d.c. and a.c. supplies up to and including 1 000 V at 50 Hz.

The performance requirements have been covered in IS 16104 : 2012 'd.c. or a.c. supplied electronic controlgear for LED modules — Preference requirements'.

This standard, along with the other parts make up IS 15885 series on safety of lamp controlgear. In this standard while referring to any of the clauses of IS 15885 (Part 1) : 2011 'Safety of lamp controlgear: Part 1 General requirements' specifies the extent to which such a clause is applicable and the order in which the tests are to be performed; they also include additional requirements as necessary'. All parts which make up IS 15885 (Part 2) are self-contained and therefore do not include references to each other.

Where the requirements of any of the clauses of IS 15885 (Part 1) are referred to in this standard by the phrase "The requirements of Clause '...' of IS 15885 (Part 1) apply", this phrase is interpreted as meaning that all requirements of the clause in question of Part 1 shall apply, except any, which are clearly inapplicable to the specific type of lamp control gear covered by this particular standard.

This standard is based on IEC 61347-2-13, Ed 1 2006-05 'Lamp controlgear — Part 2-13: Particular requirements for d.c. or a.c. supplied electronic controlgear for LED modules' and IEC 34C/901A/DC 'd.c. or a.c. supplied electronic control gear for LED modules' issued by the International Electrotechnical Commission (IEC).

For the purpose of deciding whether a particular requirement of this standard is complied with, the final value, observed or calculated expressing the result of a test, shall be rounded off in accordance with IS 2 : 1960 'Rules for rounding off numerical values (*revised*)'. The number of significant places retained in the rounded off value should be the same as that of the specified value in this standard.

Indian Standard

SAFETY OF LAMP CONTROLGEAR

PART 2 PARTICULAR REQUIREMENTS

Section 13 d.c. or a.c. Supplied Electronic Controlgear for LED Modules

1 SCOPE

This standard (Part 2/Sec 13) specifies particular safety requirements for electronic control gear for use on d.c. supplies up to and including 1 000 V and a.c. supplies up to and including 1 000 V at 50 Hz and at an output frequency which can deviate from the supply frequency, associated with LED modules.

Control gear for LED modules specified in this standard are designed to provide constant voltage or current at SELV or higher voltages. Deviations from the pure voltage and current types do not exclude the gear from this standard.

The Annexes A, B, C, D, E, F, G, H and L of IS 15885 (Part 1) : 2011 ‘Safety of lamp controlgear: Part 1 General requirements’ which are applicable according to this Part and Section and using the word ‘lamp’ are understood to also comprise LED modules.

Particular requirements for SELV control gears are given in Annex I.

Performance requirements shall be covered by a separate standard (*see* IS 16104 : 2012 ‘d.c. or a.c. supplied electronic controlgear for LED Modules — Performance requirements’).

Plug-in control gear, being part of the luminaire, are covered as for built-in control gear by the additional requirements of the luminaire standard.

2 REFERENCES

The standards listed below contain provisions which through reference in this text, constitute provisions of this standard. At the time of publication, the editions indicated were valid. All standards are subject to revision and parties to agreements based on this standard are encouraged to investigate the possibility of applying the most recent editions of the standards listed as follows:

<i>IS No.</i>	<i>Title</i>
2500 (Part 1) : 2000	Sampling procedures for inspection by attributes: Part 1 Sampling schemes indexed by acceptance quality limit (AQL) for lot-by-lot inspection

*IS No.**Title*

15885 (Part 1) :
2011 Safety of lamp controlgear: Part 1
General requirements

3 TERMINOLOGY

For the purpose of this standard, the definitions given in IS 15885 (Part 1) and the following shall apply.

3.1 Electronic Controlgear for LED Modules — Unit inserted between the supply and one or more LED modules which serves to supply the LED module(s) with its (their) rated voltage or rated current. The unit may consist of one or more separate components and may include means for dimming, correcting the power factor and suppressing radio interference.

3.2 d.c. or a.c. Supplied Controlgear — Controlgear that includes stabilizing elements for operating one or more LED module(s).

3.3 SELV Controlgear — Controlgear providing a SELV output isolated from the supply mains by means such as a safety isolating transformer.

3.4 Associated Controlgear — Controlgear designed to supply specific appliance(s) or equipment, incorporated or not incorporated.

NOTE — An example of an associated control gear is an electronic control gear within an emergency unit where it is assigned in a one-to-one relation to battery driven ballast.

3.5 Plug-in Controlgear — Controlgear incorporated in an enclosure provided with an integral plug as the means of connection of the electrical supply.

3.6 Rated Output Voltage for Constant Voltage Controlgear — Output voltage, at rated supply voltage, rated frequency and at rated output power, assigned to the control gear.

3.7 Rated Output Current for Constant Current Controlgear — Output current, at rated supply voltage, rated frequency and at rated output power, assigned to the control gear.

3.8 Light Emitting Diode (LED) — Solid state device

IS 15885 (Part 2/Sec 13) : 2012

embodying a *p-n* junction, emitting optical radiation when excited by an electric current.

NOTE — This definition is independent from the existence of enclosure(s) and of terminals.

3.9 LED Module — Unit supplied as a light source. In addition to one or more LEDs it may contain further components, for example optical, electrical, mechanical and/or electronic.

3.10 Maximum Output Voltage — Maximum voltage which can occur between the output terminals for constant current controlgear in any load condition.

3.11 Acceptance Test — Tests carried out on samples taken from a lot for the acceptance of the lot.

4 GENERAL REQUIREMENTS

The requirements of 4 of IS 15885 (Part 1) shall apply, together with the following additional requirements.

Controlgears providing SELV shall comply with the requirements of Annex I. This includes insulation resistance, electric strength, creepage distances and clearance between primary and secondary circuits.

Controlgear which are not of the pure voltage and current types are tested according to the requirements of either a voltage source or a current source, whichever comes closer to the electrical behaviour of the controlgear.

5 GENERAL NOTES ON TESTS

The requirements of 5 of IS 15885 (Part 1) shall apply along with the following additional requirements.

The following number of specimens shall be submitted for testing:

- a) One unit for the tests of 6 to 12 and 15 to 21; and
- b) One unit for the tests of 14 (additional units or components, where necessary, may be required in consultation with the manufacturer).

6 CLASSIFICATION

Control gears are classified according to the method of installation given in 6 of IS 15885 (Part 1) and according to,

- a) protection against electric shock;
- b) auto-wound control gear;
- c) separating control gears;
- d) isolating control gears; and
- e) SELV control gears.

7 MARKING

7.1 Mandatory Marking

Control gears, other than integral control gear, shall be clearly and durably marked, in accordance with the requirements of 7.2 of IS 15885 (Part 1), with the following mandatory markings.

7.1 (a), (b), (c), (d), (e), (f), (k), (m) and (t) of IS 15885 (Part 1) together with the following:

- a) For constant voltage types: rated output voltage;
- b) For constant current types: rated output current; and
- c) If applicable: an indication that the control gear is suitable for operation with LED modules only.

7.2 Information to be Provided, if Applicable

In addition to the above mandatory markings, the following information, if applicable, shall be given either on the control gear, or be made available in the manufacturer's catalogue :

- a) 7.1 (h), (j) and (s) of IS 15885 (Part 1); and
- b) Mention whether the controlgear has mains-connected windings.

7.3 BIS Certification Marking

The controlgear may also be marked with the Standard Mark.

7.3.1 The use of the Standard Mark is governed by the provisions of the *Bureau of Indian Standards Act, 1986* and the Rules and Regulations made thereunder. The details of conditions under which the licence for the use of the Standard Mark may be granted to manufacturers or producers may be obtained from the Bureau of Indian Standards.

8 PROTECTION AGAINST ACCIDENTAL CONTACT WITH LIVE PARTS

The requirements of 10 of IS 15885 (Part 1) shall apply.

9 TERMINALS

The requirements of 8 of IS 15885 (Part 1) shall apply.

10 PROVISIONS FOR PROTECTIVE EARTHING

The requirements of 9 of IS 15885 (Part 1) shall apply.

11 MOISTURE RESISTANCE AND INSULATION

The requirements of 11 of IS 15885 (Part 1) shall apply.

12 ELECTRIC STRENGTH

The requirements of **12** of IS 15885 (Part 1) shall apply.

13 THERMAL ENDURANCE TEST FOR WINDINGS OF BALLASTS

The requirements of **13** of IS 15885 (Part 1) is not applicable.

14 FAULT CONDITIONS

The requirements of **14** of IS 15885 (Part 1) shall apply, together with the following additional requirements.

In the case of control gear provided with the marking, the requirements specified in Annex C shall be fulfilled.

15 TRANSFORMER HEATING

SELV, isolating and separating control gears shall be tested according to **L-6** and **L-7** of IS 15885 (Part 1), where the requirements for control gears providing SELV are valid also for separating and isolating control gears.

For SELV control gears, the output voltage shall not exceed the limits given in **10.4** of IS 15885 (Part 1), during the tests of **15.1** and **15.2**.

15.1 Normal Operation

The requirements of **L-6** of IS 15885 (Part 1) shall apply, together with the following additional requirement.

For built-in and integral control gears tests shall be made under conditions such that the convertors is brought to t_c , as reached under normal operation at rated supply voltage.

15.2 Abnormal Operation

The requirements of **L-7** of IS 15885 (Part 1) shall apply. In addition the following test at any voltage between 90 percent and 110 percent of the rated supply voltage shall be performed if relevant, with the control gear operating according to the manufacturer's instructions (including heatsinks, if specified) for 1 h.

Connect double the LED modules or equivalent load for which the control gear is designed,

- a) in parallel to the output terminals, for constant voltage output types; and
- b) in series to the output terminals, for the constant current output types.

During and at the end of the tests specified above, the control gear shall show no defect impairing safety, nor shall any smoke or flammable gases be produced.

16 CONSTRUCTION

The requirements of **15** of IS 15885 (Part 1) shall apply.

17 CREEPAGE DISTANCES AND CLEARANCES

Unless otherwise specified in **14** the requirements of **16** of IS 15885 (Part 1) shall apply.

18 SCREWS, CURRENT-CARRYING PARTS AND CONNECTIONS

The requirements of **17** of IS 15885 (Part 1) shall apply.

19 RESISTANCE TO HEAT, FIRE AND TRACKING

The requirements of **18** of IS 15885 (Part 1) shall apply.

20 RESISTANCE TO CORROSION

The requirements of **19** of IS 15885 (Part 1) shall apply.

21 TESTS

21.1 Classification of Tests

21.1.1 Type Tests

The following shall constitute the type tests to be carried out on selected sample of controlgear, sample being drawn preferably from regular production lot:

- a) Marking (*see 7*);
- b) Protection against accidental contact with live parts (*see 8*);
- c) Terminals (*see 9*);
- d) Provisions for protective earthing (*see 10*);
- e) Moisture resistance (*see 11*);
- f) Electric strength (*see 12*);
- g) Thermal endurance test for windings of ballasts (*see 13*);
- h) Fault conditions (*see 14*);
- j) Transformer heating (*see 15*);
- k) Construction (*see 16*);
- m) Creepage distances and clearances (*see 17*);
- n) Screws, current-carrying parts and connections (*see 18*);
- p) Resistance to heat, fire and tracking (*see 19*); and
- q) Resistance to corrosion (*see 20*).

21.2 Acceptance Test

The sampling plan for acceptance tests shall be as specified in IS 2500 (Part 1). The following shall constitute as acceptance tests:

- a) Marking (*see 7*);

IS 15885 (Part 2/Sec 13) : 2012

- | | |
|--|--|
| b) Protection against accidental contact with live parts (<i>see 8</i>); | e) Moisture resistance (<i>see 11</i>); |
| c) Terminals (<i>see 9</i>); | f) electric strength (<i>see 12</i>); |
| d) Provisions for protective earthing (<i>see 10</i>); | g) Fault conditions (<i>see 14</i>); and |
| | h) Transformer heating (<i>see 15</i>). |

ANNEX A

(Clause 1)

TEST TO ESTABLISH WHETHER A CONDUCTIVE PART IS A LIVE PART WHICH MAY CAUSE AN ELECTRIC SHOCK

The requirements of Annex A of IS 15885 (Part 1) shall apply.

ANNEX B

(Clause 1)

PARTICULAR REQUIREMENTS FOR THERMALLY PROTECTED LAMP CONTROL GEAR

The requirements of Annex B of IS 15885 (Part 1) is not applicable.

ANNEX C

(Clauses 1 and 14)

PARTICULAR REQUIREMENTS FOR ELECTRONIC LAMP CONTROL GEAR WITH MEANS OF PROTECTION AGAINST OVERHEATING

The requirements of Annex C of IS 15885 (Part 1) shall apply.

ANNEX D

(Clause 1)

REQUIREMENTS FOR CARRYING OUT THE HEATING TESTS OF THERMALLY PROTECTED LAMP CONTROL GEAR

The requirements of Annex D of IS 15885 (Part 1) shall apply.

ANNEX E

(Clause 1)

USE OF CONSTANT S OTHER THAN 4 500 IN T_w TESTS

The requirements of Annex E of IS 15885 (Part 1) shall apply.

ANNEX F
(*Clause 1*)

DRAUGHT-PROOF ENCLOSURE

The requirements of Annex F of IS 15885 (Part 1) shall apply.

ANNEX G
(*Clause 1*)

EXPLANATION OF THE DERIVATION OF THE VALUES OF PULSE VOLTAGES

The requirements of Annex G of IS 15885 (Part 1) are not applicable.

ANNEX H
(*Clause 1*)

TESTS

The requirements of Annex H of IS 15885 (Part 1) shall apply.

ANNEX I
(*Clauses 1 and 4*)

**PARTICULAR ADDITIONAL REQUIREMENTS FOR SELV d.c. OR a.c. SUPPLIED ELECTRONIC
CONTROL GEARS FOR LED MODULES**

The requirements are under consideration.

Bureau of Indian Standards

BIS is a statutory institution established under the *Bureau of Indian Standards Act, 1986* to promote harmonious development of the activities of standardization, marking and quality certification of goods and attending to connected matters in the country.

Copyright

BIS has the copyright of all its publications. No part of these publications may be reproduced in any form without the prior permission in writing of BIS. This does not preclude the free use, in the course of implementing the standard, of necessary details, such as symbols and sizes, type or grade designations. Enquiries relating to copyright be addressed to the Director (Publications), BIS.

Review of Indian Standards

Amendments are issued to standards as the need arises on the basis of comments. Standards are also reviewed periodically; a standard along with amendments is reaffirmed when such review indicates that no changes are needed; if the review indicates that changes are needed, it is taken up for revision. Users of Indian Standards should ascertain that they are in possession of the latest amendments or edition by referring to the latest issue of 'BIS Catalogue' and 'Standards : Monthly Additions'.

This Indian Standard has been developed from Doc No.: ETD 23 (6302).

Amendments Issued Since Publication

Amend No.	Date of Issue	Text Affected

BUREAU OF INDIAN STANDARDS

Headquarters:

Manak Bhavan, 9 Bahadur Shah Zafar Marg, New Delhi 110002

Telephones : 2323 0131, 2323 3375, 2323 9402

Website: www.bis.org.in

Regional Offices:

Telephones

Central : Manak Bhavan, 9 Bahadur Shah Zafar Marg
NEW DELHI 110002

{ 2323 7617
2323 3841

Eastern : 1/14 C.I.T. Scheme VII M, V. I. P. Road, Kankurgachi
KOLKATA 700054

{ 2337 8499, 2337 8561
2337 8626, 2337 9120

Northern : SCO 335-336, Sector 34-A, CHANDIGARH 160022

{ 60 3843
60 9285

Southern : C.I.T. Campus, IV Cross Road, CHENNAI 600113

{ 2254 1216, 2254 1442
2254 2519, 2254 2315

Western : Manakalaya, E9 MIDC, Marol, Andheri (East)
MUMBAI 400093

{ 2832 9295, 2832 7858
2832 7891, 2832 7892

Branches: AHMEDABAD. BANGALORE. BHOPAL. BHUBANESHWAR. COIMBATORE. DEHRADUN. FARIDABAD. GHAZIABAD. GUWAHATI. HYDERABAD. JAIPUR. KANPUR. LUCKNOW. NAGPUR. PARWANOO. PATNA. PUNE. RAJKOT. THIRUVANANTHAPURAM. VISAKHAPATNAM.